

# PHILIPS

## EasyKey

7000 Series

Smart video door lock

DDL702



## Remote video monitoring

### Visible security

Adopted with a PIR, when someone moves around within 3 meters at the front door, the Philips DDL702-1HW will capture a photo or a video and push it to the App via Wi-Fi connection, allowing you to know who's at the door anytime.

### Realtime's on Wi-Fi connection

The DDL702-1HW smart video lock makes real-time online via the Wi-Fi connection. After binding the Philips EasyKey App, you can view the lock activity history and encrypted information, remotely send temporary PIN codes, and view the real-time situation at the door by clicking the video button.

### Two-way intercom

When the visitor presses the doorbell, a message will push to the APP instantly. If the APP runs in the foreground, it will receive a call reminder; if the APP runs in the background, it will receive a message. You could start a two-way intercom by tapping the message box to connect with the App.

When the doorbell rings, the video lock will automatically record the video, so you won't miss any visitor information even when you are not home.

### PIR human body detection

Adopted with the PIR, when someone moves around the front door within 3 meters, the AI humanoid detection algorithm will identify abnormal dynamics by instantly capturing a photo or a video, and simultaneously pushing a message to the APP through the encrypted cloud server. Now that it allows you to fully manage the dynamics at the front door and avoid security risks.



\* Data source: SenseTime facial recognition laboratory.

\* Facial recognition unlocking will be off when the battery level is low.

## C-grade lock cylinder

The lock cylinder is the key component that controls the opening of the lock. DDL702-1HW's C-grade lock cylinder employs multiple anti-theft technologies with a unique design of pin tumbler and vane structure. As the time for technical lock-picking resistance is more than 270 mins, enhanced security is assured.

## Multiple alert function

Featured multiple alerts of anti-dismantling, abnormal bolt, outside forced locking, and low battery level reminder, Philips DDL702-1HW instantly safeguards the family and reminds you of the lock status. Now that is peace of mind.

## Fully automatic mortise

Philips DDL702-1HW utilizes a fully automatic mortise. Without the need for extra action, the bolt will spontaneously pop up upon closing the door. If the door is not locked fitly, it will trigger an alert to remind you of the door lock status.

## ● Specifications

General Characteristics		System mode	General mode	PIR motion alert
Material	Zinc alloy		Dual verification mode	Networking Remotely add a PIN code
Finishing	Baking varnish	<b>Electrical Power</b>		
	Electroplating	Power supply	Li-polymer battery	Remotely setting lock parameters
Color	Copper red	Battery life	3 months*	Remotely check access records
Handle	Push-pull handle	Emergency power supply	5V Powerbank	Share temporary PIN code
Mortise	Full auto mortise	<b>Operating Environment</b>		
	C-grade lock cylinder	Temperature	-20°C~+60°C	Doorbell & Video Visitor's arrival notification
Fingerprint sensor	Semiconductor sensor	Humidity	15%RH-93%RH	Surveillance of all front door activities after Wi-Fi connected
Connectivity	Wi-Fi	<b>Installation Requirements</b>		
<b>Access Solution</b>		Door thickness	38-60mm	Two-way talk via App
Outdoor unlocking	Fingerprint		60-90mm	Emergency escape Indoor fast opening mortise
	PIN code		90-120mm	Update OTA & Batch update via rear interface
	Mechanical key		Other ranges*	Indicators Low battery level indicator
Indoor unlocking	Temporary PIN code	Door opening direction	Left-in/Left-out, Right-in/Right-out	Lock status indicator
	Rotary knob	Door type	Wooden/Copper/Security door	Mute status indicator
	Button	<b>Key Features</b>		
Infrared sensor		Locking function	Indoor deadlock System lock	System lock indicator
		Safety	Hidden PIN code Outside forced lock Dual verification	Outside forced lock indicator
		Alert	Anti-dismantling alert Outside forced lock alert Abnormal latch bolt alert	Indoor infrared sensor unlock indicator
				On/Off indoor infrared sensor indicator
<b>Capacity</b>				Doorbell indicator
Fingerprint	100			Voice guide Human voice guide
Master PIN code	1			
User PIN code	20			
One-time PIN code	1			
<b>Modes</b>				
Operation mode	Manual mode			
	Auto mode			

\* 3 months: The laboratory data, the actual battery life will vary depending on the using scenes.

\* Other range: Please consult our service agent or an authorized dealer.

Product specifications are subject to modify without prior notice.

The Philips and the Philips Shield Emblem are registered trademarks and property of Koninklijke Philips N.V. and are used under license.

